Hämeenkatu 9
05800 HYVINKÄÄ
Tel. 020 789 5900
www.fescon.fi

NANTEN EP ACCELERATOR



Product description

Liquid accelerator (Component C) for use in solvent-free Nanten epoxy coatings, designed to reduce the curing time of epoxy-based products.

Applications

- Used in conjunction with patch repairs and priming layers
- Enables faster curing time

Instructions

Mixing

The A-component of Nanten SL Bio epoxy coating must first be mixed to a uniform consistency. A small portion of Part A is set aside – refer to the Mixing Ratio section for guidance. Nanten EP Accelerator is added to Part A and mixed thoroughly for one minute. Then, Part B is added and mixed for two minutes, avoiding air entrapment in the mixture. Finally, the mixture is poured into a clean container and mixed for an additional one minute, again avoiding air entrapment.

Mixing ratio

The use of the additive accelerates the curing reaction. It is recommended to prepare no more than 2–4 litres of coating mixture at a time.
When used with patch repairs and priming layers, Nanten EP Accelerator should be added at a maximum of 3% by weight of the total coating mixture.
Example 1: 0.75 litres of Nanten SL Bio Part A + 3% (= 42 g = 43.3 ml) Nanten EP Accelerator + 0.25 litres of Nanten SL Bio Part B
Example 2: 2 litres of Nanten HM Bio Part A + 3% (= 99 g = 102 ml) Nanten EP Accelerator + 1 litre of Nanten HM Bio Part B

Waste handling

Storage and handling of waste
See the separate storage and disposal instructions https://www.fescon.fi/en/material-bank

Hämeenkatu 9
05800 HYVINKÄÄ
Tel. 020 789 5900
www.fescon.fi

Technical information

Package size	1 l
Storage	+5°C to +25°C, protected from light, maximum storage time 12 months
Density	0.97 kg/l

Remember to consult the Maintenance Instructions for Coated Floors and the product Safety Data Sheet on our website at www.fescon.fi, or request a copy by calling +358 9 274 7970. Although the technical details provided in this product description are based on our best knowledge and experience, the information above should always be regarded as indicative. The user is responsible for verifying the suitability of the product for the intended application. If the instructions are not followed, the user assumes full responsibility for any resulting damage or consequences. Limitation of liability, product use notes and restrictions: Please familiarize yourself with Fescon Oy's general terms of delivery and the design and work instructions related to the product.